



**828MP-1**

FM Sidemount Antennas

828MP Series

These FM sidemount antennas are designed for FM broadcasting applications which require circular polarization and low windloads.

The stainless steel design ensures that the antenna will give years of trouble free performance in the most hostile environments. The higher power series are pressurized to add further environmental protection.

Elements will tolerate a degree of light icing but for more severe environments, 828 antennas can be supplied with radomes. Contact RFS for details.

All 828 series antennas can be arrayed in any number of levels to suit most applications. The parallel feed system facilitates the customization of null fill and beam tilt to suit customer requirements.

The standard 828 antenna series is for high power applications; for medium power select the 828MP series. Both series have three models designed for bandwidth of 10 MHz. Additional factory tuning is available to achieve superior return loss specifications.

A wideband series of the 828 antenna, 828HP, covers the entire FM band from 88 to 108 MHz and utilizes half wavelength spacing.

The wide variety of possible configurations ensures that this antenna range meets the needs of most users on both price and performance.



828MP Series showing 828-8 antenna

**FEATURES / BENEFITS**

- Rugged stainless steel construction for maximum corrosion protection
- Low downward radiation
- Various power ratings available
- Mixed polarization
- Broadband operation to facilitate antenna sharing
- 828 and 828HP series pressurized
- 828MP series designed specifically for un-pressurized operation
- Low windload to minimize tower or mast costs
- Radomes are an available option for all 828 series
- Temperature range -40 to +60 degrees C available.

**Technical features**

**STRUCTURE**

<b>Product Line</b>		Antenna TV
<b>Product Type</b>		Band II (VHF) 828MP-1 FM Sidemount Antennas

**ELECTRICAL SPECIFICATIONS**

<b>Frequency Range</b>	MHz	88 - 108
<b>Operating Frequency Ranges</b>	MHz	88 - 98
		94 - 104
		98 - 108
<b>Polarization</b>		Circular
<b>Gain per Plane of Polarization</b>	dBd	-1.8
<b>Return Loss</b>	dB	20 Note 1
<b>Power Rating</b>	kW	3
<b>Impedance (unbalanced)</b>	$\Omega$	50




**MECHANICAL SPECIFICATIONS**

Number of Levels		1
Input Connector		7-16 DIN
Mounting (Standard)	mm (in)	Brackets for 60mm (2-3/8") pole mount
Effective Area Front (full antenna) No Ice	m <sup>2</sup> (ft <sup>2</sup> )	0.05 (0.54) Single Bay
Effective Area Front (full antenna) with 12.5mm(0.5") Radial Ice	m <sup>2</sup> (ft <sup>2</sup> )	0.05 (0.54) Single Bay
Effective Area Side (full antenna) No Ice	m <sup>2</sup> (ft <sup>2</sup> )	0.19 (2.04) Single Bay
Effective Area Side (full antenna) 12.5mm (0.5") Radial Ice	m <sup>2</sup> (ft <sup>2</sup> )	0.19 (2.04) Single Bay
Weight	kg (lb)	7.5 (17) Single Bay

**PACKAGING INFORMATION**

Shipping Weight, Kg (lb)	kg (lb)	7.5 ()
--------------------------	---------	--------

Image not found or type unknown



External Document Links

Notes

**Note 1** Arrays are factory tuned for a broadband performance and a return loss of 20dB across the specified bandwidth is achieved. Optional factory tuning for optimum narrow band performance will achieve a 30dB return loss over +/- 1MHz from the specified frequency. Arrays may be supplied un-tuned with a resulting return loss of 14dB.

**Note 2** Array power ratings are limited by the radiator and power divider input connectors used. Typical limits are : 7-16 DIN 3.5kW, 7/8" EIA 5kW, 1-5/8" EIA 10kW and 3-1/8" EIA 40kW.

**Note 3** Mechanical specifications: For 828MP and 828 the single bay Effective Area Front is 0.05 sq m (0.54 sq ft), Effective Area Side is 0.19 sq m (2.04 sq ft). For 828HP, single bay Effective Area Front is 0.06 sq m (0.65 sq ft), Effective Area Side is 0.25 sq m (2.35 sq ft).